

# S3000

## DLIVE REMOTE CONTROL SURFACE

The S3000 is a 20 fader dLive S Class remote control surface with a 12" capacitive touchscreen.

The S3000 can control any MixRack / Mainframe. Up to 4 control Surfaces can be connected to a single MixRack / Mainframe.

20 faders & 20 rotaries are freely assignable in 6 layers on the surface, giving 120 "control strips."

The S3000 can be connected with a single CAT5e cable or a dual redundant mode Cat5e cable to the Mixrack/Mainframe. Two 128x128 channel option slots are available on the back.

With the S3000 surface you can choose the control for the end-user through custom layouts and user permissions.



### Key Features

- Mix and match with any MixRack
- Custom fader layout
- Self-locking Ethercon connectors
- Local I/O and extra DX port
- No noise, fanless design

### Benefits

- 12" Capacitive touchscreen
- 2x 128x128 I/O ports for extra audio networking
- User permissions
- 120 Control strips
- 26 User assignable keys